

PAC-5000



PUBLIC ADDRESS COMBINATION AMPLIFIER



FEATURES

- 250Watt, 2Ways, 24-Zone Digital Amplifier
- 24 Output select switch & Group select key, Simultaneous broadcast
- FM Tuner, 1CDP(MP3+WMA) installed
- Mic. for Emergency broadcasting installed
- PC remote control and Program broadcasting through RS-232C
- Priority : EM > Fire > Tel In > Remote Mic > Mic 1 > Mic 2~6 > Siren > Chime > Ringer

SPECIFICATIONS

- ELECTRICAL *0dB=0.775Vrms
 - Input Sensitivity
 - Mic Input 1~6(Balance).....-50dB ±3dB
 - Aux Input 1~2(Unbalance)-10dB ±3dB
 - Aux Input 3(Unbalance)+4dB ±3dB
 - Remote Mic Station Input 1~4(Balance)0dB ±3dB
 - T. H. DLess than 1%
 - S/NMore than 90dB
 - Output Power250W/2CH
 - Pre Out & Rec Out Sensitivity
 - Pre Out(Balance)0dB ±3dB
 - Re Out(Unbalance)0dB ±3dB
- GENERAL
 - Power Source100~120VAC or 220~240VAC; 50/60Hz, 24VDC (supplied AC mains transformer depends on local requirements)
 - Weight22kg/48.5lb
 - Dimensions482(W)x177(H)x369(D)mm
19(W)x6.9(H)x14.5(D)in