

SERVICE

MANUAL

P

R

E

AMPLIFIER

PP-9214

interM

ELECTRICAL PARTS LIST

Ref No.	Part No.	Description	Value
INPUT MIC B'D (4003494800)			
CH3, 4, 5, 6, 7, 8 (THE SAME AS CH 2) - Ref No: 3XX, 4XX, 5XX, 6XX, 7XX, 8XX			
AN951	4355828207	CON ASS'Y 3P (POWER)	ASS'Y 3P
AN121	4355828104	CON ASS'Y 2P (INPUT)	ASS'Y 2P
C102-103	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C106-107			
C104-105	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
C110 C112	3529050311-A	CAP CE SL 5P 50V M AXIAL	5P
C111	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
C113-114 C133	3539103521-A	CAP CE YF 10000PF 25V Z AXIAL	0.01
C952 C956	3408210261	CAP RSG 1000UF 35V SNAP 16 P	1000/35
C957	3409210141-T	CAP AF RSG 100UF 25V 6 P	100/25
C951	3419582268	CAP AF HS 8200UF 35V 35 P LUG	8200/35
C953	3509103450-T	CAP CE 0.01UF 500V Z	0.01/500
C954-955	3509104530-T	CAP CE F 0.1UF 50V Z	0.1/50
CN100	4428592306	CONNECTOR WAFER GW-06	GW-06
CN122A	4428595002	LW5267/LWB0640/2.5MM-02P	LW5267-02
CN953A	4428592304	CONNECTOR WAFER GW-04	GW-04
CN954 CN1154	4428595002	LW5267/LWB0640/2.5MM-02P	LW5267-02
CN953B			
CN950	4428595003	LW5267/LWB0640/2.5MM-03P	LW5267-03
CNT	4678699411	CNT PLUG 1P	CNT PLUG
D952	2058100983	DIODE BRIDGEPBL302P/KBL403/404	PBL302P
D951	2058304107	DIODE SCHOTTKY SB-150 (SR105)	SB150
FB100-101	2648609970	EMI BEAD FILTER BFS2550 AOF	FILTER
IC100	2118010432	IC NJM2068DD JRC	2068DD
IC950	2128611000	IC KA7818 COMMON	7818
IC950 HEAT SINK	7505299320	HEAT SINK(45MM) REG TR	HEAT SINK
JK101	4438193610	XLR JACK(F)3P(E203A0031N)	MIC1
JK950	4438094610	DC TERMINAL 2P	DC 24V
R104-105	3009153973	RES CF 15K 1/5W J N	15K
R108-109	3009331973	RES CF 330 1/5W J N	330
R111-112	3009473973	RES CF 47K 1/5W J N	47K
R102-103	3009682973	RES CF 6.8K 1/5W J N	6.8K
R110	3009683973	RES CF 68K 1/5W J N	68K
R953	3039102572-F	RES MO 1K 2W J N	1K 2W
R950	3039479572-F	RES MO 4.7 2W J N	4.7 2W
R954	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10
F200	5508111637	FUSE 51S 20MM 400MA/250V U/C	120V 50Hz (E) 220V 60Hz (DOM) 240V 50Hz (D)
	5508411639	FUSE#218T 20MM 400MA/250V UCSK	220V 50Hz (M)
	5508411634	FUSE 218T 20MM 400MA/250V UCSK	220V 60Hz (R) 230-240V 50Hz (C)
F200 FUSE CLIP	4458999110	FUSE CLIP 5*20	FUSE CLIP 5*20

CH 2

AN221	4355828104	CON ASS'Y 2P (INPUT)	ASS'Y 2P
C202-203	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C206-207			
C214-216			
C218-219			
C204-205	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
C210 C213	3529050311-A	CAP CE SL 5P 50V M AXIAL	5P
C211	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
C217	3529330311-A	CAP CE SL 33PF 50V J AXIAL	33P
C235	3539103521-A	CAP CE YF 10000PF 25V Z AXIAL	0.01
Q200	2008606998-T	KTD1302-AT	D1302
FB200-201	2648609970	EMI BEAD FILTER BFS2550 AOF	FILTER
IC200	2118010432	IC NJM2068DD JRC	2068DD
JK201	4438193610	XLR JACK(F)3P(E203A0031N)	XLR JACK
R213-214 R216	3009103973	RES CF 10K 1/5W J N	10K
R204-205	3009153973	RES CF 15K 1/5W J N	15K
R236	3009272973	RES CF 2.7K 1/5W J N	2.7K
R208-209	3009331973	RES CF 330 1/5W J N	330
R206-207	3009333973	RES CF 33K 1/5W J N	33K
R237-238	3009334973	RES CF 330K 1/5W J N	330K
R211-212	3009473973	RES CF 47K 1/5W J N	47K
R217-218			
R219	3009564973	RES CF 560K 1/5W J N	560K
R202-203	3009682973	RES CF 6.8K 1/5W J N	6.8K
R210	3009683973	RES CF 68K 1/5W J N	68K
R215	3009822973	RES CF 8.2K 1/5W J N	8.2K

INPUT LINE B'D (4003494810)

CH3, 4, 5, 6, 7, 8 - Ref No: 3XX, 4XX, 5XX, 6XX, 7XX, 8XX

AN100	4355827701	CON ASS'Y 6P (SG)	ASS'Y 6P
C208-209	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C200-201	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
C234	3539103521-A	CAP CE YF 10000PF 25V Z AXIAL	0.01
JK200	4438097310	JACK PHONE 4P	PHONE JACK
R200-201	3009153973	RES CF 15K 1/5W J N	15K

PRIORITY JACK B'D (4003494820)

AN1101 AN1201	4355827912	CON ASS'Y 4P (STR)	ASS'Y 4P
C1101 C1201	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C1130 C1230	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
C1131 C1229	3539103521-A	CAP CE YF 10000PF 25V Z AXIAL	0.01
C1231			
CN122B	4428595002	LW5267/LWB0640/2.5MM-02P	LW5267-02
JK1100-1101	4438097310	JACK PHONE 4P	PHONE JACK
JK1200-1201			
R1100 R1200	3009153973	RES CF 15K 1/5W J N	15K
R1132 R1230	3009272973	RES CF 2.7K 1/5W J N	2.7K
R1131 R1232	3009562973	RES CF 5.6K 1/5W J N	5.6K
SW150	4628992410	SW PUSH SPUN19X1M011 (SUA29)	PUSH SW

OUTPUT JACK B'D (4003494830)

AN115	4428592304	CONNECTOR WAFER GW-04	GW-04
AN1154	4355827810	CON ASS'Y 2P GND (BLK)	ASS'Y 2P
C1400-1407	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
CN901 CN1001	4428592204	CONNECTOR WAFER GA-04	GA-04
CN1152			
CN754B	4428592306	CONNECTOR WAFER GW-06	GW-06
GND-B	4355828708	RING TERMINAL ASS'Y 1P (BLU)	ASS'Y 1P
JK1400-1401	4408194310	XLR JACK (M) E503A0150N	XLR JACK
JK1405-1406	4438192210	PHONEL JACK (5P) MOLD	PHONE JACK
JK1408-1409			
JK1402-1403			
JK1404 JK1407	4438194510	RCA JACK BOARD 2P (24MM)	RCA JACK
R1408 R1410	3009100973	RES CF 10 1/5W J N	10
R1412-1415	3009153973	RES CF 15K 1/5W J N	15K
R1401 R1403	3009473973	RES CF 47K 1/5W J N	47K
R1406-1407			
R1409 R1411	3009561973	RES CF 560 1/5W J N	560
R1400 R1402	3009750973	RES CF 75 1/5W JN	75
R1404-1405			

LED B'D (4003494840)

AN1153	4355821500	CONNECTOR ASS'Y 4P (LED)	ASS'Y 4P
AN1152	4355828314	CON ASS'Y 4P (INSERT)	ASS'Y 4P
AN1555	4355828405	CON ASS'Y 4P (LED)	ASS'Y 4P
AN953	4355828912	CON ASS'Y 6P (PUANTOM)	ASS'Y 6P
C1301	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C1302-1305	3409247973-T	CAP RSE 4.7UF 50V (5*5)MX-200	4.7/50
D1300	2058502120	DIODE ZENER UZ-12BM(1N5242B)	12BM
IC1300-1301	2118030405	KIA6966S	6966
LD1300	2300030105	LED LTL-16KHR-021A LITEON	RED
LD1305-1306			
LD1310-1311			
LD1301-1304	2300032105	LED LTL-16KG-021A LITEON	GRN
LD1307-1309			
R1302	3009100973	RES CF 10 1/5W J N	10
R1309 R1317	3009101973	RES CF 100 1/5W J N	100
R1301	3009102973	RES CF 1K 1/5W J N	1K
R1304-1308	3009152973	RES CF 1.5K 1/5W J N	1.5K
R1312-1316			
R1303	3009182973	RES CF 1.8K 1/5W J N	1.8K
R1311 R1319	3009331973	RES CF 330 1/5W J N	330
R1320-1321	3009563973	RES CF 56K 1/5W J N	56K
R1310 R1318	3009823973	RES CF 82K 1/5W J N	82K
VR1300-1301	3228077610	VR RS45111A600113A (RSI12)	10KA
SW950	4628991310	SW PUSH SPEA122SCO11(SUD40)	PUSH SW

AC INLET B'D (4003494850)

AC1	4448599010	AC INLET (B'D IN TYPE)	AC220V/60Hz
C950	3549103107	CAP DE2F3KH103MA4B	0.01
CN955 CN900	4428593603	LOCK WAFER 2 LW-1143-03P	1143-03
GND	4355828807	RING TERMINAL ASS'Y LM-9212	ASS'Y 1P
F100	5508111637	FUSE 51S 20MM 400MA/250V U/C	120V 50Hz (E) 220V 60Hz (DOM) 240V 50Hz (D)
	5508411639	FUSE#218T 20MM 400MA/250V UCSK	220V 50Hz (M)
	5508411634	FUSE 218T 20MM 400MA/250V UCSK	220V 60Hz (R) 230~240V 50Hz (C)
F100 HOLDER	4458999210	FAU-0031.3577 SCHURTER PU-3210	FUSE HOLDER

POWER SW B'D (4003494860)

AN954	4355827813	CON ASS'Y 2P GND (BLK)	ASS'Y 2P
AN955	4428593603	LOCK WAFER 2 LW-1143-03P	1143-03
S1	4628988610	SW POWER SDDF3PATL011 (SP278)	POWER SW

OUTPUT B'D (4003494870)

C13 C18	3409210071-T	CAP AF RSG 10UF 50V 5 P	10/50
C2 C7 C10 C17 C20	3409222141-T	CAP AF RSG 220UF 25V J 8 P	220/25
C1 C3-4 C6 C9 C11-12 C14	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C5 C8 C15-16	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
CN951	4428592303	CONNECTOR WAFER GW-03	GW-03
CN1153 CN1155	4428592304	CONNECTOR WAFER GW-04	GW-04
CN754A	4428592306	CONNECTOR WAFER GW-06	GW-06
CN750	4428592510	WAFER BOX TPHB03-1419-10A	WAFER BOX-10
IC1-2	2118220988	IC NJM 4580D	4580D
GND-A	4355829212	CNT ASS'Y 1P GND	ASS'Y 1P
R11-12 R17-18	3009103973	RES CF 10K 1/5W J N	10K
R1-2 R7-8	3009182973	RES CF 1.8K 1/5W J N	1.8K
R9-10	3009471973	RES CF 470 1/5W J N	470
R3-6 R13-16	3009473973	RES CF 47K 1/5W J N	47K
R19	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10

MONO CH1 B'D (4003494700)

C132 C150-151	3409210141-T	CAP AF RSG 100UF 25V 6 P	100/25
C120 C158 C160	3409222141-T	CAP AF RSG 220UF 25V J 8 P	220/25
C122-124 C126	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C131 C153-154 C127-129	3409247971-T	CAP AF RSG 4.7UF 50V 5 P	4.7/50
C152	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
C125	3529220311-A	CAP CE SL 22PF 50V J AXIAL	22P
C121	3529470311-A	CAP CE SL 47PF 50V J AXIAL	47P
C156-157 C159	3609103120-T	CAP MA 0.01UF 100V	0.01(M)

C155	3609104120-T	CAP MA 0.1UF 100V J	0.1(M)
CN122	4355828000	CON ASS'Y 4P (MUTE)	ASS'Y 4P
CN120	4428592810	WAFER BOX 10P TPHAB03-1419-10A	WAFER BOX-10
CN121	4428594902	LA5268/LAB0640/2.5MM-02P	LA5268-02
D121 D150-155	2058304100	DIODE IN4148M	1N4148
D120	2058501076	DIODE ZENER UZ-7.5B(1N5236B)	7.5BM
IC120	2118010432	IC NJM2068DD JRC	2068DD
IC150	2118010590	IC NJM4558D JRC	4558D
LD120	2300030105	LED LTL-16KHR-021A LITEON	RED
Q150-152	2008606104-T	TR NPN KTC3198-Y-AT TO-92	C3198Y
Q120	2008613000-T	TR NPN 2SD1111 (SANYO,NEC)	2SD1111
R124-125 R129	3009103973	RES CF 10K 1/5W J N	10K
R157			
R132	3009105973	RES CF 1M 1/5W J N	1M
R121	3009121973	RES CF 120 1/5W J N	120
R152	3009154973	RES CF 150K 1/5W J N	150K
R134	3009182973	RES CF 1.8K 1/5W J N	1.8K
R130-131 R162	3009183973	RES CF 18K 1/5W J N	18K
R155	3009222973	RES CF 2.2K 1/5W J N	2.2K
R156	3009225973	RES CF 2.2M 1/5W J N	2.2M
R133	3009274973	RES CF 270K 1/5W J N	270K
R158 R161	3009330973	RES CF 33 1/5W J N	33
R159	3009333973	RES CF 33K 1/5W J N	33K
R120	3009392973	RES CF 3.9K 1/5W J N	3.9K
R160 R163	3009393973	RES CF 39K 1/5W J N	39K
R128	3009472973	RES CF 4.7K 1/5W J N	4.7K
R122-123	3009473973	RES CF 47K 1/5W J N	47K
R126-127 R150			
R153-154			
R135	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10
VR101	3228078110	VR RK11K112010723A (ROM22)	20KA
VR100	3238092210	VR RK11K112000323A (ROZ91)	20KA
SW100-101	4628992410	SW PUSH SPUN19X1M011 (SUA29)	PUSH SW

MONO CH2,3,4,5,6,7,8 B'D (4003494710,20,30,4003494600,10,20,30)

CH3, 4, 5, 6, 7, 8 B'D - Ref No: 3XX, 4XX, 5XX, 6XX, 7XX, 8XX

C232	3409210141-T	CAP AF RSG 100UF 25V 6 P	100/25
C220	3409222141-T	CAP AF RSG 220UF 25V J 8 P	220/25
C222-224 C226	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C231			
C227-229	3409247971-T	CAP AF RSG 4.7UF 50V 5 P	4.7/50
C225	3529220311-A	CAP CE SL 22PF 50V J AXIAL	22P
C221	3529470311-A	CAP CE SL 47PF 50V J AXIAL	47P
CN220	4428592810	WAFER BOX 10P TPHAB03-1419-10A	WAFER BOX-10
CN221	4428594902	LA5268/LAB0640/2.5MM-02P	LA5268-02
D221	2058304100	DIODE IN4148M	1N4148
D220	2058501076	DIODE ZENER UZ-7.5B(1N5236B)	7.5BM
IC220	2118010432	IC NJM2068DD JRC	2068DD
LD220	2300030105	LED LTL-16KHR-021A LITEON	RED
Q220	2008613000-T	TR NPN 2SD1111 (SANYO,NEC)	2SD1111
R224-225 R229	3009103973	RES CF 10K 1/5W J N	10K

R232	3009105973	RES CF 1M 1/5W J N	1M
R221	3009121973	RES CF 120 1/5W J N	120
R234	3009182973	RES CF 1.8K 1/5W J N	1.8K
R230-231	3009183973	RES CF 18K 1/5W J N	18K
R233	3009274973	RES CF 270K 1/5W J N	270K
R220	3009392973	RES CF 3.9K 1/5W J N	3.9K
R228	3009472973	RES CF 4.7K 1/5W J N	4.7K
R222-223	3009473973	RES CF 47K 1/5W J N	47K
R226-227			
R235	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10
VR201	3228078110	VR RK11K112010723A (ROM22)	20KA
VR200	3238092210	VR RK11K112000323A (ROZ91)	20KA
SW200-201	4628992410	SW PUSH SPUN19X1M011 (SUA29)	PUSH SW

PRIORITY 1, 2 B'D (4003494740, 4003494640)

PRIORITY 2 B'D - Ref No: 12XX

AN115A	4428594902	LA5268/LAB0640/2.5MM-02P	LA5268-02
C1159			
C1106-1107	3409210141-T	CAP AF RSG 100UF 25V 6 P	100/25
C1116			
C1161-1162			
C1150	3409222141-T	CAP AF RSG 220UF 25V J 8 P	220/25
C1102 C1110	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C1114-1115			
C1153-1154			
C1160			
C1105	3409247971-T	CAP AF RSG 4.7UF 50V 5 P	4.7/50
C1152	3509221231-A	CAP CE B 220PF 50V K AXIAL	220P
C1103 C1158	3509471231-A	CAP CE B 470PF 50V K AXIAL	470P
C1104 C1109	3409210071-T	CAP AF RSG 10UF 50V 5 P	10/50
C1156	3529050311-A	CAP CE SL 5P 50V M AXIAL	5P
C1151 C1155	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
C1108	3529330311-A	CAP CE SL 33PF 50V J AXIAL	33P
C1112	3609103120-T	CAP MA 0.01UF 100V	0.01(M)
C1111 C1113	3609104120-T	CAP MA 0.1UF 100V J	0.1(M)
C1157	3609472120-T	CAP MA 0.0047UF 100V J	0.0047(M)
CN1101	4428592204	CONNECTOR WAFER GA-04	GA-04
CN1100	4428592810	WAFER BOX 10P TPHAB03-1419-10A	WAFER BOX-10
D1101-1104	2058304100	DIODE IN4148M	1N4148
D1110			
IC1111	2118010432	IC NJM2068DD JRC	2068DD
IC1110	2118010590	IC NJM4558D JRC	4558D
Q1101-1102	2008606104-T	TR NPN KTC3198-Y-AT TO-92	C3198Y
Q1110			
R1101	3009101973	RES CF 100 1/5W J N	100
R1102	3009102973	RES CF 1K 1/5W J N	1K
R1155	3009106973	RES CF 10M 1/5W J N	10M
R1103	3009122973	RES CF 1.2K 1/5W J N	1.2K
R1156-1157	3009124973	RES CF 120K 1/5W J N	120K
R1104	3009182973	RES CF 1.8K 1/5W J N	1.8K
R1112	3009225973	RES CF 2.2M 1/5W J N	2.2M

R1153-1154	3009272973	RES CF 2.7K 1/5W J N	2.7K
R1108	3009274973	RES CF 270K 1/5W J N	270K
R1114	3009330973	RES CF 33 1/5W J N	33
R1150	3009333973	RES CF 33K 1/5W J N	33K
R1113	3009393973	RES CF 39K 1/5W J N	39K
R1117-1118	3009394973	RES CF 390K 1/5W J N	390K
R1105-1107	3009473973	RES CF 47K 1/5W J N	47K
R1109-1111			
R1151-1152			
R1158-1159			
R1115-1116	3009562973	RES CF 5.6K 1/5W J N	5.6K
R1120-1121	3009563973	RES CF 56K 1/5W J N	56K
R1119	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10
VR1153	3228078110	VR RK11K112010723A (ROM22)	20KA
VR1150-1152	3238092410	VR RK11K116010653B (ROL14)	50KB

STEREO 1, 2 B'D (4003494750, 4003494650)

STEREO 2 B'D - Ref No: 10XX

C922-924	3409210141-T	CAP AF RSG 100UF 25V 6 P	100/25
C920-921	3409222071-T	CAP AF RSG 22UF 50V 5 P	22/50
C925-926			
C902-905	3409247041-T	CAP AF RSG 47UF 25V 5 P	47/25
C908-913			
C916-919			
C906-907	3509102231-A	CAP CE YB 1000PF 50V K AXIAL	1000P
C914-915	3529100311-A	CAP CE SL 10PF 50V J AXIAL	10P
CN901	4428592204	CONNECTOR WAFER GA-04	GA-04
CN9100	4428592810	WAFER BOX 10P TPHAB03-1419-10A	WAFER BOX-10
D900-901	2058010101	DIODE IN 60	1N60
IC900	2118010432	IC NJM2068DD JRC	2068DD
IC901	2118010590	IC NJM4558D JRC	4558D
Q900-901	2008606998-T	KTD1302-AT	D1302
Q903-904			
R902-903	3009103973	RES CF 10K 1/5W J N	10K
R916-917			
R924-925			
R918-919	3009113973	RES CF 11K 1/5W J N	11K
R908-909	3009133973	RES CF 13K 1/5W J N	13K
R904 R936	3009181973	RES CF 180 1/5W J N	180
R926-927	3009183973	RES CF 18K 1/5W J N	18K
R906-907	3009184973	RES CF 180K 1/5W J N	180K
R930-931	3009272973	RES CF 2.7K 1/5W J N	2.7K
R910-911	3009333973	RES CF 33K 1/5W J N	33K
R922-923	3009472973	RES CF 4.7K 1/5W J N	4.7K
R914-915	3009473973	RES CF 47K 1/5W J N	47K
R920-921			
R912-913	3009563973	RES CF 56K 1/5W J N	56K
R928-929	3009564973	RES CF 560K 1/5W J N	560K
R905 R935	3009681973	RES CF 680 1/5W J N	680
R934 R937	3009821973	RES CF 820 1/5W J N	820
R900	3089100275	RES NFR 10 1/4W J R PHILKO	FR 10

VR900	3228081210	VR RK14K122010723A (RO995)	20KA*2
SW902	3238089610	S/W SLIDE SSAF123NC011(SSN29)	SLIDE SW
SW900-901	4628992410	SW PUSH SPUN19X1M011 (SUA29)	PUSH SW
ASS'Y			
CONNECTOR	4355828509	CON ASS'Y 6P	ASS'Y 6P
	4355828612	CON ASS'Y 2P (POWER)	ASS'Y 2P
	4355829011	CON ASS'Y 4P	ASS'Y 4P
	4355829100	CON ASS'Y 4P	ASS'Y 4P
	4355829300	MASS CON ASS'Y 10P	ASS'Y 10P
FUSE CARRIER	4458999410	FUSE CARRIER FEU0031.1663 SUT	FUSE CARRIER
	4458999210	FAU-0031.3577 SCHURTER PU-3210	FUSE CARRIER
POWER TRANS	2828072300	POWER TRANS PP-9214 220V	120V 50Hz (E)
	2828072310	POWER TRANS PP-9214 220V	220V 60Hz (DOM)
	2828072320	TRANS POWER 235V PP-9214	220V 50Hz (M) 220V 60Hz (R) 230~240V 50Hz (C) 240V 50Hz (D)
AC CORD	4308999310	AC CORD UL 3 (INLET)	120V 50Hz (E)
	4308988610	AC POWER CORD CCC	220V 50Hz (M)
	4308997310	AC CORD DOME 3-CORES	220V 60Hz (DOM)
	4308999410	AC CORD V+VII6A-250VHOVV-F3G	220V 60Hz (R)
	4308996710	AC CORD (WITHOUT PLUG)	230~240V 50Hz (C)
	4308998000	AC CORD POWER FOR SAA	240V 50Hz (D)

COMPANY	INTER. M	APPLICANT	PROJECT	REVISED NUMBER AND DATE	DRAWN	CHECKED	APPROVED	NOTE	SHEET NO.	SCHMATIC DIAGRAM
TYPE CODE	1	2	3	4	5	6	7	8	9	MODEL : PP-9214
APPROVED DATE	1	2	3	4	5	6	7	8	9	

